

ABB (PVS) blue'Log Driver



DESCRIPTION OF FUNCTIONS

Driver: blue'Log driver for supporting ABB PVS inverters.

COMMUNICATION

Max. number of string inverters:	blue'Log X-1000	blue'Log X-3000	blue'Log X-6000
	50 *	100 **	100 **
Communication interface:	RS485, Ethernet		
Bus speed:	19200 bps		
Protocol (transmission):	8N1, TCP		

*Maximum of 31 inverters can be managed per bus interface. Connection of MX module RS485/422 is possible as an option. (Please consider the software features of your blue'Log base module. Please take a look in the data sheet of blue'Log.)

**MX module RS485/422 is necessary because up to 31 inverters can be managed per bus interface. (Please consider the software features of your blue'Log base module. Please take a look in the data sheet of blue'Log.)

POWER CONTROL

Active power control:	Yes
Reactive power control:	Yes***

Active/reactive power control is not supported by all inverter types. An exact list is available from the inverter manufacturer.

***Please consider the software features of your blue'Log base module. Please take a look in the data sheet of blue'Log.

MEASUREMENT VALUES RECORDED

E_DAY	Daily energy
E_TOTAL	Total energy
ERROR	Error status
F_AC	Grid frequency
I_AC (phase 1, 2, 3)	AC current (phase 1, 2, 3)
I_DC (string A, B, C...)	DC current (string A, B, C)
P_AC	AC active power
Q_AC	Reactive power
STATE	Operating status
T_WR	Inverter temperature
U_AC (phase 1, 2, 3)	AC voltage (phase 1, 2, 3)
U_AC_L1L2	Phase to phase voltage L1-L2
U_AC_L2L3	Phase to phase voltage L2-L3
U_AC_L3L1	Phase to phase voltage L3-L1
U_DC (string A, B, C...)	DC voltage (string A, B, C)

The actually recorded values may vary due to the inverter model or the inverter firmware.

SUPPORTED INVERTERS

PVS series: PVS300 PVS800

Please contact Sales for details of compatibility with inverters not listed.
Telephone +49 (0)821 34666 - 80
E-Mail sales@meteocontrol.com

meteocontrol GmbH | Spicherer Straße 48 | 86157 Augsburg | Germany | phone +49 (0)821 34666 - 0 | fax +49 (0)821 34666 - 11
email info@meteocontrol.com | web www.meteocontrol.com